Basic Radar 2: Fundamentals of Radar Signals

Roger H. Varney

¹Center for Geospace Studies SRI International

July 26, 2016

R. H. Varney (SRI) Radar Signals July 26, 2016 1 / 43

Stochastic Processes

2 / 43

- 1 Timeseries and Fourier Analysis
- Pulsed-Doppler Radar

Fourier Analysis

- 3 Probability Theory and Stochastic Processes
- Overspread Targets

Continuous Fourier Transform

$$\mathcal{F}\left\{f(t)
ight\} = \int_{-\infty}^{\infty} f(t)e^{-j\omega t} dt \qquad \mathcal{F}^{-1}\left\{F(\omega)
ight\} = rac{1}{2\pi}\int_{-\infty}^{\infty} F(\omega)e^{j\omega t} d\omega$$

Stochastic Processes

Properties:

- Exists when $\int_{-\infty}^{\infty} |f(t)|^2 dt$ converges
- Linearity $\mathcal{F}\{\alpha f(t) + \beta g(t)\} = \alpha \mathcal{F}\{f(t)\} + \beta \mathcal{F}\{g(t)\}$
- Time reversal $\mathcal{F}\{f(-t)\}=\mathcal{F}\{f(t)\}^*$
- Time Delay $\mathcal{F}\left\{f(t-t_0)\right\} = e^{-j\omega t_0}\mathcal{F}\left\{f(t)\right\}$
- Convolution Theorem:

$$g(t) = f(t) * h(t) = \int_{-\infty}^{\infty} f(t')h(t - t') dt'$$
$$\mathcal{F}\{g(t)\} = \mathcal{F}\{f(t)\} \times \mathcal{F}\{h(t)\}$$

Duality Between Time and Frequency

Fourier transform is a unitary operator: $\mathcal{F}^{-1} = \frac{1}{2\pi} \mathcal{F}^*$.

All properties have an dual

- Frequency reversal $\mathcal{F}^{-1}\{F(-\omega)\}=\mathcal{F}^{-1}\{F(\omega)\}^*$
- Frequency shift $\mathcal{F}^{-1}\{F(\omega-\omega_0)\}=e^{j\omega_0t}\mathcal{F}^{-1}\{F(\omega)\}$
- Dual Convolution Theorem:

$$G(\omega) = F(\omega) * H(\omega) = \int_{-\infty}^{\infty} F(\omega') H(\omega - \omega') d\omega'$$
$$\mathcal{F}^{-1} \{G(\omega)\} = 2\pi \mathcal{F}^{-1} \{F(\omega)\} \times \mathcal{F}^{-1} \{H(\omega)\}$$

Uncertainty principle (Gabor Limit):

$$\left(\int_{-\infty}^{\infty} t^2 |f(t)|^2 \ dt\right) \left(\int_{-\infty}^{\infty} \omega^2 |F(\omega)|^2 \ d\omega\right) \geq \frac{1}{16\pi^2} \left(\int_{-\infty}^{\infty} |f(t)|^2 \ dt\right)^2$$

Narrow in time \leftrightarrow Wide in frequency Wide in time \leftrightarrow Narrow in frequency

Discrete-Time Fourier Transform

Suppose I sample data with sampling period T such that $f_n = f(nT)$. The DTFT is defined as

DTFT
$$\{f\} = \sum_{n=-\infty}^{\infty} f_n e^{-j\omega nT}$$

DTFT⁻¹ $\{F(\omega)\} = \frac{T}{2\pi} \int_{-\frac{\pi}{T}}^{\frac{\pi}{T}} F(\omega) e^{j\omega nT} d\omega$

- The DTFT maps a discrete sequence onto a function of continuous frequency
- The DTFT is $\frac{2\pi}{T}$ -periodic in ω since $e^{-j\omega nT}=e^{-j\left(\omega+\frac{2\pi}{T}\right)nT}$.
- The DTFT is related to the CFT by:

DTFT
$$\{f\} = \mathcal{F}\left\{\sum_{-\infty}^{\infty} f(nT)\delta(t - nT)\right\}$$

Discrete Fourier Transform

Given N discrete samples:

$$F_k = \sum_{n=0}^{N-1} f_n e^{-2\pi j \frac{nk}{N}} \quad k \in [0, N-1]$$
 Forward DFT
$$f_n = \frac{1}{N} \sum_{k=0}^{N-1} F_k e^{2\pi j \frac{nk}{N}} \quad n \in [0, N-1]$$
 Inverse DFT

- The Fast Fourier Transform (FFT) is an algorithm for computing the DFT that is $\mathcal{O}(N \log N)$
- The DFT is a discrete sampling of the DTFT.
- If $f_n = f(nT)$ for sampling period T, then the corresponding set of discrete frequencies are

$$\omega_k = 2\pi \frac{k}{NT}$$

• Frequency resolution is $\Delta \omega = \frac{2\pi}{NT}$

R. H. Varney (SRI)

Radar Signals

7 / 43

Sampling and Aliasing

Periodicity of complex exponentials:

$$e^{2\pi j\frac{nk}{N}} = e^{2\pi j\frac{nk}{N} + 2\pi jm} \quad \forall m \in \mathbb{Z}$$

From this it follows that

$$F_k = \sum_{n=0}^{N-1} f_n e^{-2\pi j \frac{nTk}{NT}} = \sum_{n=0}^{N-1} f_n e^{-2\pi j \frac{nTk + mnTN}{NT}}$$
$$\omega_k = 2\pi \left(\frac{k}{NT} + \frac{m}{T}\right)$$

For example, with T=2 ms, $\frac{1}{T}=500$ Hz:

 $\cdots \leftrightarrow -925 \text{ Hz} \leftrightarrow -425 \text{ Hz} \leftrightarrow 75 \text{ Hz} \leftrightarrow 575 \text{ Hz} \leftrightarrow 1075 \text{ Hz} \leftrightarrow \cdots$

- The DFT returns frequencies from 0 to $\frac{1}{7}$ by default. A common convention is to report the spectrum from $-\frac{1}{2T}$ to $\frac{1}{2T}$ (fftshift).
- Nyquist Sampling Theorem: All signal frequencies must be $|\omega| < 2\pi \frac{1}{2T}$ for the DFT and DTFT to avoid frequency aliasing.


R. H. Varney (SRI) Radar Signals July 26, 2016

Overspread Targets

8 / 43

Baseband Sampling

Fourier Analysis



R. H. Varney (SRI) Radar Signals July 26, 2016

Windowing and Frequency Resolution

What are the ramifications of using a finite length segement of data in the DFT?

$$F_k = \sum_{n=0}^{N-1} f_n e^{-j\omega_k nT}$$
 DFT
$$= \sum_{n=-\infty}^{\infty} f_n r_n^N e^{-j\omega_k nT}$$
 DTFT

where the length N rectangle function is:


$$r_n^N = \begin{cases} 1 & 0 \le n < N \\ 0 & \text{otherwise} \end{cases}$$

By the convolution theorem for the DTFT:

DTFT
$$\left\{ f \times r^N \right\} = \text{DTFT} \left\{ f \right\} * \text{DTFT} \left\{ r^N \right\}$$

$$\text{DTFT} \left\{ r^N \right\} = e^{-j\frac{N-1}{2}\omega T} \frac{\sin\left(\frac{N}{2}\omega T\right)}{\sin\left(\frac{1}{2}\omega T\right)}$$

Width of Dirichlet kernel is related to NT.



9 / 43

R. H. Varney (SRI) Radar Signals July 26, 2016

Zero-padded Fourier Transforms


What happens if I try to sample a finer grid of frequencies than the standard DFT?

$$F_k' = \sum_{n=0}^{N-1} f_n e^{-2\pi j \frac{nk}{K}} \quad k \in [0, K-1], K > N$$

This is equivalent to zero padding the original sequence, then taking a standard DFT.

$$f'_n = \begin{cases} f_n & n < N \\ 0 & N < n < K \end{cases}$$

$$F'_k = \sum_{n=0}^{K-1} f'_n e^{-2\pi j \frac{nk}{K}} \quad k \in [0, K-1]$$



The length N rectangular window sets the real frequency resolution. Zero padding just interpolates the windowed spectrum.


R. H. Varney (SRI)

Radar Signals

Effects of Other Window Functions

Chose tapered window weights w_n to combat effects of rectangular window

$$F_k = \sum_{n=0}^{N-1} w_n f_n e^{-j\omega_k nT}$$



Digital Filters


Finite Impulse Response Filter (FIR) Infinite Impulse Response Filter (IIR)

$$y_k = \sum_{n=0}^{N-1} h_n x_{k-n}$$
 $y_k = \sum_{n=0}^{N-1} h_n x_{k-n} + \sum_{m=1}^{M-1} g_m y_{k-m}$

- FIR used extensively in radar signal processing.
- Impulse response is the output when $x_n = \delta_n$. For FIR filters this is h_n .
- Frequency response of an FIR filter:

$$H(\omega) = \sum_{n=0}^{N-1} h_n e^{-j\omega nT}$$
 DTFT of Impulse Response

Example: 255-tap FIR Blackman filter used at PFISR




12 / 43

R. H. Varney (SRI) Radar Signals July 26, 2016

Range-Time Diagram

Range

Fourier Analysis



Time

Interpret the 1-D receiver voltage as a function of time as if it were a function of both range and time.

- v_n^k is the sample of range gate n after pulse k
- *n* is the "fast-time" dimension (range), and *k* is the "slow-time" dimension (time)
- Range gate *n* is at a range of $R = \frac{ct_n}{2}$
- Each slow-time sample is separated by one interpulse period (IPP)

Range-Doppler Processing

Range-Time Data Array:

$$\begin{pmatrix} v_0^0 & v_0^1 & \cdots & v_0^{K-1} \\ v_1^0 & v_1^1 & \cdots & v_1^{K-1} \\ \vdots & \vdots & \vdots & \vdots \\ v_{N-1}^0 & v_{N-1}^1 & \cdots & v_{N-1}^{K-1} \end{pmatrix}$$

Take an FFT along the slow-time dimension for each range

$$u_n^m = \sum_{k=0}^{K-1} v_n^k e^{2\pi j \frac{mk}{K}}$$

Range-Frequency Data Array:

Stochastic Processes

$$\begin{pmatrix} u_0^0 & u_0^1 & \cdots & u_0^{K-1} \\ u_1^0 & u_1^1 & \cdots & u_1^{K-1} \\ \vdots & \vdots & \vdots & \vdots \\ u_{N-1}^0 & u_{N-1}^1 & \cdots & u_{N-1}^{K-1} \end{pmatrix}$$

Physically $|u_n^m|^2$ is proportional to the received power at

- Range $r_n = \frac{ct_n}{2}$
- Frequency $\omega_m = 2\pi \frac{m}{K_{\text{TIRP}}}$
- Dopper velocity $V_m = \frac{c}{2} \frac{\omega_m}{2\pi f_0}$

Doppler Aliasing

Fourier Analysis

The FFTs are performed along the slow time dimension, hence the effective sampling rate is $\tau_{\rm IPP}$.


In order to avoid aliasing in the FFTs for each range:

$$au_{
m IPP} < rac{1}{2f_{
m max}}$$

Short IPPs implies pulses very close together.

Is there any problem with having pulses very close together?

Range Aliasing



R. H. Varney (SRI)

Radar Signals

Underspread and Overspread Targets

Shorter IPP:

- Captures wide bandwidth
- Leads to range aliasing

Longer IPP:

- Captures a large range extent
- Leads to frequency aliasing

If an IPP exists than can avoid both range and frequency aliasing the target is underspread. Otherwise it is overspread.

Underspread Example: D-region ISR at 450 MHz

- Ranges 0-90 km, Frequencies ± 75 Hz
- 2 ms IPP gives 300 km unambiguous range, ± 250 Hz frequencies

Overspread Example: F-region ISR at 450 MHz

- Ranges 0-600 km, Frequencies ±10 kHz
- \bullet 600 km unambiguous range requires a > 4 ms IPP
- ± 10 kHz unambiguous frequencies requires a $< 50~\mu \mathrm{s}$ IPP

R. H. Varney (SRI) Radar Signals July 26, 2016 17 / 43

Gaussian Random Variables

Fourier Analysis

A Gaussian random variable X has the following probability density function (Normal Distribution):

$$p(x) = \frac{1}{\sqrt{2\pi}\sigma} \exp\left\{-\frac{x-\mu}{2\sigma^2}\right\}$$

$$E\{X\} = \mu$$

$$Var\{X\} = E\left\{(X-\mu)^2\right\} = E\left\{X^2\right\} - \mu^2 = \sigma^2$$

A vector of random variables $\mathbf{X} = [X_0 X_1 X_2 \cdots X_{N-1}]^T$ is jointly Gaussian if each in they have the joint PDF

$$p(\mathbf{x}) = \frac{1}{(2\pi)^{\frac{N}{2}} |C|^{\frac{1}{2}}} \exp\left\{-\frac{1}{2} [\mathbf{x} - \mu]^T C^{-1} [\mathbf{x} - \mu]\right\}$$

$$E\{\mathbf{X}\} = \mu$$

$$Cov\{\mathbf{X}\} = E\left\{ [\mathbf{X} - \mu] [\mathbf{X} - \mu]^T \right\} = C$$

R. H. Varney (SRI)

Overspread Targets

Properties of Jointly Gaussian Random Variables

Linear combinations:

$$Z = \alpha X + \beta Y + \gamma \quad E\{Z\} = \alpha E\{X\} + \beta E\{Y\} + \gamma$$

$$Var\{Z\} = \alpha^2 Var\{X\} + \beta^2 Var\{Y\} + 2\alpha\beta Cov\{X,Y\}$$

• Matrix generalization:

$$\mathbf{Y} = \mathbf{AX} + \mathbf{b}$$
 $E\{\mathbf{Y}\} = \mathbf{AX} + \mathbf{b}$ $Cov\{\mathbf{Y}\} = \mathbf{A}Cov\{\mathbf{X}\}\mathbf{A}^T$

Special cases for zero mean random variables:

Odd moments are zero:

$$E\{V_1\} = E\{V_1V_2V_3\} = E\{V_1V_2V_3V_4V_5\} = \cdots = 0$$

- Fourth moment theorem: $E\{V_1V_2V_3V_4\} =$ $E\{V_1V_2\}E\{V_3V_4\}+E\{V_1V_3\}E\{V_2V_4\}+E\{V_1V_4\}E\{V_2V_3\}$
- General even moment theorem (Isserlis' Theorem) $E\{V_1V_2\cdots V_{2n-1}V_{2n}\} = \sum \prod E\{V_iV_i\}$

R. H. Varney (SRI) Radar Signals July 26, 2016 19 / 43

Complex Gaussian Random Variables

ISR signals are complex valued, zero mean, and random phase.

$$V = V_R + jV_I \qquad E\{V_R\} = E\{V_I\} = 0$$

$$E\{VV^*\} = \sigma^2 \qquad E\{V_RV_I\} = 0 \qquad Cov\left\{\begin{pmatrix} V_R \\ V_I \end{pmatrix}\right\} = \frac{1}{2}\begin{pmatrix} \sigma^2 & 0 \\ 0 & \sigma^2 \end{pmatrix}$$

When we talk about correlations between ISR signals

$$E\{V_1V_1^*\} = \sigma_1^2$$
 $E\{V_2V_2^*\} = \sigma_2^2$
 $E\{V_1V_2^*\} = \rho = \rho_R + j\rho_I$

What we really mean is

$$Cov \left\{ \begin{pmatrix} V_{1R} \\ V_{1I} \\ V_{2R} \\ V_{2I} \end{pmatrix} \right\} = \frac{1}{2} \begin{pmatrix} \sigma_1^2 & 0 & \rho_R & -\rho_I \\ 0 & \sigma_1^2 & \rho_I & \rho_R \\ \rho_R & \rho_I & \sigma_2^2 & 0 \\ -\rho_i & \rho_R & 0 & \sigma_2^2 \end{pmatrix}$$

R. H. Varney (SRI) Radar Signals

20 / 43

Stochastic Processes: Definitions and Terminology

- Stochastic Process (aka Random Process): V(t) where value at every time is a random variable
- Gaussian Stochastic Process:

Fourier Analysis

- ullet PDF of each V(t) is a Gaussian distribution (aka normal distribution)
- Joint PDF of any subset of samples of V(t) is a jointly Gaussian distribution (aka Multivariate Normal Distribution)
- Moments of a Stochastic Process:
 - Mean: $\bar{V}(t) = E\{V(t)\}$
 - Autocorrelation: $R(t, t \tau) = E\{V(t)V^*(t \tau)\}$
 - Autocovariance:

$$C(t, t - \tau) = E\left\{ \left[V(t) - \bar{V}(t) \right] \left[V^*(t - \tau) - \bar{V}^*(t - \tau) \right] \right\} = R(t, t - \tau) - \bar{V}(t)\bar{V}^*(t - \tau)$$

- (Wide Sense) Stationary Stochastic Process
 - $\bar{V}(t) = \bar{V}$ is independent of t
 - $R(t, t \tau) = R(\tau)$ is independent of t
- ISR signals are Gaussian, zero mean, and stationary as long as the ionospheric state parameters are constant.

R. H. Varney (SRI) Radar Signals July 26, 2016 21 / 43

Examples of Discrete Stochastic Process

Gaussian white noise W_n :


$$ar{W} = 0$$
 $R_{\ell} = E\left\{W_n W_{n-\ell}^*\right\} = \begin{cases} \sigma_0^2 & \ell = 0\\ 0 & \ell \neq 0 \end{cases}$

3-point running sum of Gaussian white noise

$$V_{n} = W_{n} + W_{n-1} + W_{n-2}$$
 $R_{\ell} = E\{[W_{n} + W_{n-1} + W_{n-2}][W_{n-\ell} + W_{n-\ell-1} + W_{n-\ell-2}]^{*}\}$

$$= \begin{cases} (3 - |\ell|) \sigma_{0}^{2} & |\ell| < 3 \end{cases}$$


$$0 & |\ell| \geq 3 \end{cases}$$
The expressive model



Autoregressive model

$$Y_n = \alpha Y_{n-1} + W_n$$
 $Y_n = W_n + \alpha W_{n-1} + \alpha^2 W_{n-2} + \alpha^3 W_{n-3} + \cdots$

$$R_{\ell} = \frac{\alpha^{|\ell|}}{1 - \alpha^2} \sigma_0^2$$



Examples of Continuous Random Processes

Voltage across a warm resistor (Nyquist Noise Theorem)

$$E\{V_R(t)\} = 0 \qquad E\{V_R(t)V_R^*(t-\tau)\} = 4Rk_BT\delta(\tau)$$


Voltage across capacitor connected to a warm resistor

$$V_C(t) = \frac{1}{RC} \int_{-\infty}^t V_R(t') - V_C(t') dt'$$

$$V_C(t) = \frac{1}{RC} \int_{-\infty}^t e^{\frac{t'-t}{RC}} V_R(t') dt'$$

$$E \left\{ V_C(t) \ V_C(t-\tau) \right\} = \frac{2Rk_B T}{RC} e^{-\frac{|\tau|}{RC}}$$

Fourier Analysis



Overspread Targets

23 / 43

R. H. Varney (SRI) Radar Signals July 26, 2016

Power Spectrum

Fourier Analysis

- Fourier transform of a WSS random process does not exist since $\int_{-\infty}^{\infty} |V(t)|^2 \ dt \to \infty$
- Fourier transform of the ACF does exist, and is called the Power Spectrum.

$$S(\omega) \equiv \mathcal{F}\left\{R(\tau)\right\} = \int_{-\infty}^{\infty} R(\tau) e^{-j\omega\tau} d\tau$$

Properties of Power Spectrum:

- $S(\omega)$ is real and $S(\omega) \ge 0$ [follows from $R(\tau) = R(-\tau)^*$]
- $\int_{-\infty}^{\infty} S(\omega) \ d\omega = R(0)$ [total power]
- $\int_{\omega_1}^{\omega_2} S(\omega) \ d\omega = \text{power in the band from } \omega_1 \text{ to } \omega_2$
- If $y(t) = h(t) * x(t) \rightarrow S_Y(\omega) = |H(\omega)|^2 S_X(\omega)$ where $H(\omega) = \mathcal{F}\{h(t)\}$

R. H. Varney (SRI) Radar Signals July 26, 2016 24 / 43

Power Estimation

Given K samples v_i of a WSS random process V(t) with true power $P = R(0) = E\{V(t)V^*(t)\}$, and assuming the samples are far enough apart that they are uncorrelated Power estimator:

$$\hat{P} = \frac{1}{K} \sum_{i=0}^{K-1} v_i v_i^*$$

Expected value of power estimator:

$$E\left\{ \hat{P}\right\} =P$$
 unbiased estimator

Variance of power estimator:

$$\delta \hat{P}^2 = E\left\{ \left(\hat{P} - P \right)^2 \right\} = \frac{1}{K} P^2$$

Relative error $\frac{\delta \vec{P}}{P} = \frac{1}{\sqrt{\kappa}}$

R. H. Varney (SRI)

Radar Signals

Signal Power Estimation with Added Noise

Given K samples $v_i = s_i + n_i$, and an independently known noise power, N

$$\hat{S} = \frac{1}{K} \sum_{i=0}^{K-1} v_i v_i^* - N$$

$$E\left\{\hat{S}\right\} = S \qquad \text{unbiased estimator}$$

$$Var\left\{\hat{S}\right\} = \frac{1}{K} (S + N)^2$$

$$\frac{\delta \hat{S}}{S} = \frac{1}{\sqrt{K}} \left(1 + \frac{1}{S/N}\right)$$

For example, $\frac{\delta \hat{S}}{S} = 0.05$ with a S/N = 0.1 requires K = 484.

ACF Estimation (Pulse-to-Pulse)

Now assume pulses are taken close together and are correlated. Unbiased Estimator:

$$\hat{R}_{\ell} = \frac{1}{K - \ell} \sum_{n=\ell}^{K-1} v_n v_{n-\ell}^*$$

$$E\left\{\hat{R}_{\ell}\right\} = R_{\ell}$$

Biased Estimator:

$$\begin{split} \tilde{R}_{\ell} &= \frac{1}{K} \sum_{n=\ell}^{K-1} v_n v_{n-\ell}^* \\ E\left\{\tilde{R}_{\ell}\right\} &= \frac{K-\ell}{K} R_{\ell} \quad \text{[triangular window]} \\ Var\left\{\tilde{R}_{\ell}\right\} &= \frac{1}{K^2} \sum_{n=\ell}^{K-1} \sum_{m=\ell}^{K-1} |R_{m-n}|^2 \approx \frac{1}{K} |R_0|^2 \end{split}$$

July 26, 2016

28 / 43

Spectral Estimation (Pulse-to-Pulse Periodograms)

Given $v_0, v_1, v_2, ..., v_{K-1}$ I could compute

$$\check{V}_n = \sum_{k=0}^{K-1} v_k e^{-2\pi j \frac{nk}{K}} \quad n \in [0, K-1]$$

$$\check{S}_n = \left| \check{V}_n \right|^2$$

$$\check{K}_k = \frac{1}{K} \sum_{n=0}^{K-1} \check{S}_n e^{2\pi j \frac{nk}{K}}$$

This turns out to be biased by periodic wrap-around effects. For example:

$$K\check{R}_2 = v_2v_0^* + v_3v_1^* + \dots + v_{K-1}v_{K-3}^* + v_0v_{K-2}^* + v_1v_{K-1}^*$$

This is called a periodogram, and generally shouldn't be used.

R. H. Varney (SRI) Radar Signals

Zero-padded Periodograms


A better estimator is the zero padded periodogram:

$$\begin{split} \tilde{V}_{n} &= \sum_{k=0}^{K-1} v_{k} e^{-2\pi j \frac{nk}{2K}} \quad n \in [0, 2K - 1] \quad \tilde{S}_{n} = \left| \tilde{V}_{n} \right|^{2} \\ \tilde{R}_{k} &= \frac{1}{2K} \sum_{n=0}^{2K-1} \tilde{S}_{n} e^{2\pi j \frac{nk}{2K}} \\ &= \frac{1}{K} \sum_{n=k}^{K-1} v_{n} v_{n-k}^{*} \end{split}$$

This provides a fast way to compute the biased ACF estimator using FFTs.

- R_k is a sampled and triangularly windowed estimate of $R(\tau)$.
- \tilde{S}_n is an aliased and smoothed estimate of $S(\omega)$.

Effects of Aliasing and Windowing on Periodograms



R. H. Varney (SRI) Radar Signals July 26, 2016

30 / 43

Combining Coherent and Incoherent Integration

Divide a sequence of M pulses into L sets of K such that M = LK.

$$\tilde{R}_{\ell} = \frac{1}{L} \sum_{\ell=0}^{L-1} \frac{1}{K} \sum_{k=\ell}^{K-1} v_k v_{k-\ell}^* \quad \ell \in [0, K-1]$$

Increasing the coherent integration time K gives

- Longer lags in \tilde{R}
- ullet Higher frequency resolution in $ilde{\mathcal{S}}$

Increasing the incoherent integration time L gives

Better statistics


In general K should be long enough to capture the correlation time of the process; longer is computationally wasteful.

Unlike the coherent integration samples, the incoherent integration intervals do not need to be contiguous in time.

R. H. Varney (SRI) Radar Signals July 26, 2016

31 / 43

Double Pulse Experiment



ISR signals from disjoint altitudes are uncorrelated:

$$E\{s(h_1; t + \tau) s^*(h_2; t)\} = \begin{cases} R(h_1; \tau) & h_1 = h_2 \\ 0 & h_1 \neq h_2 \end{cases}$$
$$E\{v(t_s + \tau)v^*(t_s)\} = E\{s(h; t + \tau) s^*(h; t)\} = R(h; \tau)$$

R. H. Varney (SRI) Radar Signals July 26, 2016 32 / 43

Error Analysis of Double Pulse Experiment

Without self-clutter (dual polarization):

$$v_{1} = s(h; t + \tau) + n(t + \tau) \qquad v_{2} = s(h; t) + n(t)$$

$$\hat{R}(\tau) = \frac{1}{K} \sum_{i=0}^{K-1} v_{i1} v_{i2}^{*} \qquad E\left\{\hat{R}(\tau)\right\} = E\left\{v_{1} v_{2}^{*}\right\} = R(h; \tau)$$

$$Var\left\{\hat{R}(\tau)\right\} = \frac{1}{K} \left[E\left\{v_{1} v_{2}^{*} v_{1}^{*} v_{2}\right\} - |E\left\{v_{1} v_{2}^{*}\right\}|^{2}\right]$$

$$= \frac{1}{K} \left[E\left\{v_{1} v_{2}^{*}\right\} E\left\{v_{1}^{*} v_{2}\right\} + E\left\{v_{1} v_{1}^{*}\right\} E\left\{v_{2}^{*} v_{2}\right\} + \frac{E\left\{v_{1} v_{2}\right\} E\left\{v_{2}^{*} v_{1}^{*}\right\} - |E\left\{v_{1} v_{2}^{*}\right\}|^{2}\right]$$

$$= \frac{1}{K} E\left\{v_{1} v_{1}^{*}\right\} E\left\{v_{2}^{*} v_{2}\right\}$$

$$= \frac{1}{K} \left[S(h) + N\right]^{2} = \frac{S^{2}(h)}{K} \left[1 + \frac{1}{S(h)/N}\right]^{2}$$

R. H. Varney (SRI)

Radar Signals

Double Pulse Experiment with Self-Clutter

With self-clutter (single polarization):

$$v_{1} = s(h; t + \tau) + s\left(h + \frac{c\tau}{2}; t + \frac{\tau}{2}\right) + n(t + \tau)$$

$$v_{2} = s(h; t) + s\left(h - \frac{c\tau}{2}; t + \frac{\tau}{2}\right) + n(t)$$

$$\hat{R}(\tau) = \frac{1}{K} \sum_{i=0}^{K-1} v_{i1}v_{i2}^{*} \qquad E\left\{\hat{R}(\tau)\right\} = E\left\{v_{1}v_{2}^{*}\right\} = R(h; \tau)$$


$$Var\left\{\hat{R}(\tau)\right\} = \frac{1}{K} E\left\{v_{1}v_{1}^{*}\right\} E\left\{v_{2}^{*}v_{2}\right\}$$

$$= \frac{1}{K} \left[S(h) + S\left(h + \frac{c\tau}{2}\right) + N\right] \left[S(h) + S\left(h - \frac{c\tau}{2}\right) + N\right]$$

Signal-to-Noise ratio \rightarrow Signal-to-(Noise+Clutter) ratio


R. H. Varney (SRI) Radar Signals July 26, 2016 34 / 43

Multipulse Experiments



R. H. Varney (SRI) Radar Signals

Uncoded Long Pulse



R. H. Varney (SRI) Radar Signals July 26, 2016 36 / 43

Amplitude Ambiguity Function

After transmitting a pulse envelope s(t), the scattered signal is

$$x(t) = \int d^3\mathbf{r} \, e^{j\mathbf{k}\cdot\mathbf{r}} s\left(t - \frac{2r}{c}\right) \Delta N_e\left(\mathbf{r}, t - \frac{r}{c}\right)$$

The receiver records a filtered and sampled version of the scattered signal

$$y(t_s) = \int dt x(t) h^*(t_s - t)$$

$$= \int dt d^3 \mathbf{r} \, e^{j\mathbf{k} \cdot \mathbf{r}} s\left(t - \frac{2r}{c}\right) \Delta N_e\left(\mathbf{r}, t - \frac{r}{c}\right) h^*(t_s - t)$$

Define the amplitude ambiguity function

$$egin{aligned} W_{t_s} &\equiv s \left(t - rac{2r}{c}
ight) h^* \left(t_s - t
ight) \ y \left(t_s
ight) &= \int dt d^3 \mathbf{r} \ e^{j \mathbf{k} \cdot \mathbf{r}} W_{t_s}(t,r) \Delta N_e \left(\mathbf{r}, t - rac{r}{c}
ight) \end{aligned}$$

R. H. Varney (SRI)

Radar Signals

38 / 43

Range-Lag Ambiguity Function

When we form ACFs, we take products of samples and average:

$$\langle y\left(t_{s2}\right)y^{*}\left(t_{s1}\right)\rangle = \int dt_{1}dt_{2}d^{3}\mathbf{r}_{1}d^{3}\mathbf{r}_{2}e^{j\mathbf{k}\cdot(\mathbf{r}_{2}-\mathbf{r}_{1})}$$

$$\left\langle \Delta N_{e}\left(\mathbf{r}_{2},t_{2}-\frac{r_{2}}{c}\right)\Delta N_{e}^{*}\left(\mathbf{r}_{1},t_{1}-\frac{r_{1}}{c}\right)\right\rangle$$

$$W_{ts2}\left(t_{2},r_{2}\right)W_{ts1}^{*}\left(t_{1},r_{1}\right)$$

Change variables $t_1 = t$ $t_2 = t + \tau$ $\mathbf{r}_1 = \mathbf{r}$ $\mathbf{r}_2 = \mathbf{r} + \mathbf{r}'$ Perform \mathbf{r}' integral and take expected value


$$\left\langle y\left(t_{s2}\right)y^{*}\left(t_{s1}\right)\right\rangle =\int d\tau d^{3}\mathbf{r}\,R\left(\mathbf{k},\tau,\mathbf{r}\right)\underbrace{\int dt\,W_{ts2}\left(t+\tau,r\right)W_{ts1}^{*}\left(t,r\right)}_{W_{ts1},t_{s2}\left(\tau,r\right)}$$

The measured lag-product is the ISR ACF we want $R(\mathbf{k}, \tau, \mathbf{r})$ blurred the the range-lag ambiguity function $W_{t_{c1},t_{c2}}(\tau,r)$

R. H. Varney (SRI) Radar Signals July 26, 2016

2-D Range-lag Ambiguity Function of Long Pulse


Ambiguity function with a boxcar filter. 480 μ s long pulse, 30 μ s sampling.



R. H. Varney (SRI) Radar Signals July 26, 2016 39 / 43

Theoretical Long Pulse Examples

A particular exaggerated example using 1.5 $\rm ms$ long pulses and a profile with a sharp T_e gradient at 500 km.




R. H. Varney (SRI)

Fourier Analysis

Radar Signals

Random Codes and Alternating Codes



$$a_{0}a_{1}v_{0}v_{1}^{*} = a_{0}\left(a_{0}s_{h}^{t} + a_{1}s_{h-1}^{t+\frac{1}{2}} + a_{2}s_{h-2}^{t+1} + a_{3}s_{h-3}^{t+\frac{3}{2}}\right) \times$$

$$a_{1}\left(a_{0}s_{h+1}^{t+\frac{1}{2}} + a_{1}s_{h}^{t+1} + a_{2}s_{h-1}^{t+\frac{3}{2}} + a_{3}s_{h-2}^{t+2}\right)^{*}$$


$$E\left\{a_{0}a_{1}v_{0}v_{1}^{*}\right\} = E\left\{s_{h}^{t}s_{h}^{*t+1}\right\} + a_{0}a_{2}E\left\{s_{h-1}^{t+\frac{1}{2}}s_{h-1}^{*t+\frac{3}{2}}\right\}$$

$$+ a_{0}a_{1}a_{2}a_{3}E\left\{s_{h-2}^{t+1}s_{h-2}^{*t+2}\right\}$$

R. H. Varney (SRI) Radar Signals July 26, 2016 41 / 43

Range-lag Ambiguity Function of Alternating Codes

Ambiguity function for a boxcar filter. 480 μ s (16-baud, 30 μ s baud, 32 pulse).



Canonical ISR Experiments

- D-region: Underspread pulse-to-pulse processing
- Perpendicular to B drifts (Jicamarca): Underspread pulse-to-pulse processing
- E-region: Alternating codes, overspread processing
- F-region and topside: Uncoded long pulse, overspread processing

Active area of research: Combination modes that compute lags both within the pulse (overspread) and pulse-to-pulse (underspread) in order to estimate the properties of the D-, E-, and F-regions simultaneously.

R. H. Varney (SRI) Radar Signals July 26, 2016 43 / 43